

ОБОЗНАЧЕНИЕ СЕРДЕЧНИКОВ В СООТВЕТСТВИИ СО СТАНДАРТОМ HD 308 S2

CORE IDENTIFICATION ACC. TO HD 308 S2

КАБЕЛИ С ЗЕЛЕНО-ЖЕЛТЫМ ПРОВОДНИКОМ

Количество	Тип сердечника	Цвет сердечника
1	PE	зелено-желтый
2		
3	LNPE	коричневый, синий, зелено-желтый
4	3LPE	коричневый, черный, серый, зелено-желтый
5	3LNPE	коричневый, черный, серый, синий, зелено-желтый
≥6	NRPE	черный, пронумерованный, зелено-желтый

КАБЕЛИ БЕЗ ЗЕЛЕНО-ЖЕЛТОГО ПРОВОДНИКА КАБЕЛИ С КОНЦЕНТРИЧЕСКИМ ПРОВОДНИКОМ

Количество	Тип сердечника	Цвет сердечника
1	L	черный
2	LN	коричневый, синий
3	3L	коричневый, черный, серый
4	3LN	коричневый, черный, серый, синий
5		
≥6	NR	черный, пронумерованный

CABLES WITH GREEN-YELLOW CONDUCTOR

Core numbers	Core function	Core colour
1	PE	green-yellow
2		
3	LNPE	brown, blue, green-yellow
4	3LPE	brown, black, grey, green-yellow
5	3LNPE	brown, black, grey, blue, green-yellow
≥6	NRPE	black, numbered, green-yellow

CABLES WITHOUT GREEN-YELLOW CONDUCTOR, CABLES WITH CONCENTRIC CONDUCTOR

Core numbers	Core function	Core colour
1	L	black
2	LN	brown, blue
3	3L	brown, black, grey
4	3LN	brown, black, grey, blue
5		
≥6	NR	black, numbered